



DUAL LTE / DUAL
WI-FI MOBILE
ACCESS ROUTER



Manage this device with
Digi Remote Manager



DIGI WR54

Rugged and secure cellular router for mission critical industrial and transportation applications, including FirstNet Ready™ models for public safety networks

The versatility and performance of Digi WR54 routers make them ideal for mission critical applications requiring continuous connectivity, field longevity and edge computing. FirstNet Ready™ Digi WR54 provides secure routing and gateway functionality across wired and wireless communication networks. Local private subnets are bridged across public networks to safeguard privacy and integrity.

Digi WR54 is available with dual Wi-Fi radios to segment passenger Wi-Fi from fare collection, data, video and other applications, and offers FirstNet Ready™ models with both single and dual cellular modules. FirstNet® is a public/private partnership managed by the U.S. Dept. of Commerce that develops and operates a nationwide first responder network.

Designed to meet the demands of first responders, Digi WR54 includes concurrent and independent dual cellular interfaces that prioritize critical communications. Industrial-grade design supports the most rugged conditions, including vibration and temperature changes. An embedded Python environment also enables quick adaptation to evolving system requirements.

Four Gigabit Ethernet ports connect other IP-capable systems, each configurable as an isolated secure LAN, or all four can function as a Layer 2 switch. Digi TrustFence®, a suite of hardware and firmware features, ensures the integrity of Digi WR54 security functions. A cryptographic co-processor protects particularly sensitive information.

FEATURES AND BENEFITS

- [FirstNet Ready™](#) models include Digi WR54 A146/A246 with single or dual cellular modules
- Global models Digi WR54 A106/A206 with single or dual cellular radios
- Future-built with dual-core 880 MHz MIPS processor and PCIe 2.0 internal bus
- Segmented private vs. public data communication across dual 600 Mbps Cat 11 cellular modules
- High-speed 867 Mbps 802.11ac Wi-Fi for WAN or LAN service and dual Wi-Fi radios in Digi WR54-A112
- Cryptographic co-processor with secure key generation
- Digi Remote Manager® platform for easy setup, mass configuration and out-of-band management

APPLICATION EXAMPLE



RELATED PRODUCTS



SPECIFICATIONS

DIGI® WR54

CELLULAR

LTE – WORLDWIDE

LTE – WORLDWIDE LTE FDD: B1, B2, B3, B4, B5, B7, B8, B12, B13, B17, B20, B25, B26, B28, B29, B30 (Rx only), B66; LTE TDD: B38, B40, B41
3G HSPA+: B1, B2, B4, B5, B8
Transfer rate (max): 600 Mbps down, 75 Mbps up (Cat 11)

LTE – UNITED STATES / CANADA
(FIRSTNET READY™)

LTE FDD: B1, B2, B3, B4, B5, B7, B8, B9, B12, B13, B14, B18, B19, B20, B26, B29, B30, B32, B41, B42, B43, B46, B48, B66
3G HSPA: B1, B2, B4, B5, B6, B8, B9, B19
Transfer rate (max): 600 Mbps down, 150 Mbps up (Cat 12)

CONNECTOR

Single cellular models: (2) 50 Ω SMA (center pin: female)
Dual cellular models: (4) 50 Ω SMA (center pin: female)

SIM SLOTS

Single cellular models: (2) Mini-SIM (2FF)
Dual cellular models: (4) Mini-SIM (2FF)

SIM SECURITY

Screw-down SIM cover

WI-FI

MODULE

2 x 2 MIMO 2.4/5 GHz 802.11 a/b/g/n/ac, 867 Mbps (max); dual Wi-Fi modules in WR54-A112

HOTSPOT

Captive portal, customizable splash page

AUTHENTICATION

Basic ToS acceptance, enterprise RADIUS

THIRD-PARTY SERVICES

Content filtering, embedded advertising

MODES

Up to 4 access points and 1 client per Wi-Fi module (8+2 total)

SECURITY

None, WPA/WPA2-personal, WPA/WPA2-enterprise

CONNECTORS

2 x 50 Ω RP-SMA (center pin: male)

GPS

TECHNOLOGY

Multi-constellation: concurrent reception of up to 3 GNSS (GPS, Galileo, GLONASS, BeiDou)

SENSITIVITY

-163 dB

PROTOCOL

Protocol NMEA 0183 V2.3 sentence output

CONNECTOR

1 x 50 Ω SMA (center pin: female); +3.3 VDC active antenna drive

SOFTWARE AND MANAGEMENT

PROTOCOLS

IPv4/IPv6, DMNR, QoS, NTP, dynamic DNS, syslog

SECURITY

Stateful firewall, VPN (IPsec and OpenVPN), PKI and RADIUS

REMOTE MANAGEMENT

Digi Remote Manager® (cloud based); SNMP v1/v2c/v3

LOCAL MANAGEMENT

Web interface (HTTP/HTTPS); CLI (SSH, serial port)

MANAGEMENT/
TROUBLESHOOTING TOOLS

Protocol analyzer with PCAP for Wireshark, event and system logging (with syslog), accessible from Digi Remote Manager, SFTP or SCP

PROGRAMMING TOOLS/
ENVIRONMENTS

Python v3.5

ETHERNET

PORTS

(4) RJ-45; 10/100/1000 Mbps (auto-sensing)

SERIAL

PORTS

(1) DB9-M; RS-232 DTE
Signal support TXD, RXD, RTS, CTS, DTR, DCD, DSR, RI software (XON/XOFF), hardware supported

USB

PORTS

(1) USB 3.0 Type A connector

PHYSICAL

DIMENSIONS (L X W X H)

14.61 cm x 20.95 cm x 6.35 cm (5.75 in x 8.25 in x 2.5 in)

WEIGHT

1.5 kg (3.3 lbs)

STATUS LEDS

Power on, WWAN signal strength, WWAN service

ENCLOSURE

Die-cast aluminium / IP54

POWER REQUIREMENTS

POWER INPUT

9 - 36 VDC, 30 W minimum power source required

POWER CONSUMPTION

13 W typical (idle); 20 W typical (peak Tx/Rx)

SPECIFICATIONS

DIGI® WR54

ENVIRONMENTAL

OPERATING TEMPERATURE	-34° C to 74° C (-29° F to 165° F)
RELATIVE HUMIDITY	5% to 95% (non-condensing)

APPROVALS

CELLULAR	PTCRB, AT&T, Sprint (WR54-A146 and WR54-A246 only), Verizon
SAFETY	EN60950, EN62368
VEHICLE	ISO 7637-2/3, ISO 10605, ISO 16750-2 Pulses 4/5a/5b, SAE J1455, SAE J1113, E-Mark*
ENVIRONMENTAL	MIL-STD-810G
EMISSIONS/IMMUNITY	CE, FCC Part 15 Class B, AS/NZS CISPR 22, EN55024, EN55032

WARRANTY

PRODUCT WARRANTY	3-year**
------------------	----------

*Only on WR54-A106, WR54-A112 and WR54-A206 models.

**Standard 3-year warranty upgradeable to 5 years with purchase of a Digi Remote Manager Premier 5-year subscription applicable to the product purchased only at the time of product purchase and with product registration at that time in Digi Remote Manager.

DIGI REMOTE MANAGER®



Digi Remote Manager is the technology platform that brings networks to the next level, allowing networks — and the people who manage them — to work smarter. With Digi Remote Manager you can transform a multitude of dispersed IoT devices into a dynamic, intelligent network. Now you can easily deploy, monitor and diagnose thousands of mission-critical devices from a single point of command — on your desktop, tablet or phone. All the while, its software-defined security diligently safeguards your entire Digi ecosystem.

Learn more at www.digi.com/digi-remote-manager

CAPABILITIES

- Activate, monitor and diagnose your mission-critical devices from a single point of command and control — on your desktop or mobile app
- Schedule key operations — including firmware updates and file management — on a single device or on a group of devices, keeping your network functionality up-to-date and maintaining compliance standards
- Manage edge devices out-of-band via console terminal access
- Keep tabs on device health and connectivity across device deployments of any size
- Create detailed reports and enable real-time alerts for specified conditions
- Integrate device data through open APIs to gain deeper insights and control with third-party applications
- Report and alert on performance statistics, including connection history, signal quality, latency, data usage and packet loss

INFRASTRUCTURE

- Hosted in a commercial-grade cloud server environment that meets SOC 1®, SOC 2® and SOC 3® standards
- Superior availability, operating to 99.9% or greater
- Open APIs available to support application development

SECURITY

- More than 175 security controls in place to protect your data
- Member of the Center for Internet Security® (CIS®)
- Enables compliance with security frameworks like ISO27002, HIPAA, NIST and more
- Earned Skyhigh's CloudTrust™ Program highest rating of Enterprise-Ready

PART NUMBERS*	DIGI® WR54
WR54-A106	Digi WR54 single LTE, Wi-Fi, worldwide
WR54-A112	Digi WR54 single LTE, dual Wi-Fi, worldwide
WR54-A206	Digi WR54 dual LTE, Wi-Fi, worldwide
WR54-A146	Digi WR54 FirstNet, single LTE, Wi-Fi, North America
WR54-A246	Digi WR54 FirstNet, dual LTE, Wi-Fi, North America

PART NUMBERS	ACCESSORIES*
76002084	Digi WR54 accessory kit - single cellular
76002085	Digi WR54 accessory kit - dual cellular
76002086	Digi WR54 accessory kit - dual Wi-Fi
76002076	Digi WR54 power supply

*Sold separately, unless otherwise noted.

PART NUMBERS	DIGI REMOTE MANAGER®
DIGI-RM-STD-1YR	Digi Remote Manager Standard - 1-year subscription
DIGI-RM-PRM-1YR	Digi Remote Manager Premier - 1-year subscription
DIGI-RM-PRM-3YR	Digi Remote Manager Premier - 3-year subscription
DIGI-RM-PRM-5YR	Digi Remote Manager Premier - 5-year subscription

FOR MORE INFORMATION
PLEASE VISIT DIGI.COM

FirstNet® and FirstNet Ready™ are registered trademarks and service marks of the First Responder Network Authority.

DIGI SERVICE AND SUPPORT / You can purchase with confidence knowing that Digi is always available to serve you with expert technical support and our industry leading warranty. For detailed information visit www.digi.com/support.

© 1996-2020 Digi International Inc. All rights reserved.
All trademarks are the property of their respective owners.

91004362
D1/1120

DIGI INTERNATIONAL WORLDWIDE HQ
877-912-3444 / 952-912-3444 / www.digi.com

DIGI INTERNATIONAL GERMANY
+49-89-540-428-0

DIGI INTERNATIONAL JAPAN
+81-3-5428-0261 / www.digi-intl.co.jp

DIGI INTERNATIONAL SINGAPORE
+65-6213-5380

DIGI INTERNATIONAL CHINA
+86-21-50492199 / www.digi.com.cn

